

area.

- 2). Drill holes in the wall according to the bracket's hole positions and put the plastic screw covers into holes.
- 3). Fix the bracket with the screw into the screw cover.
- 4). Stick the back side of the detector into the bracket until it is fully inserted into the buckles.

Testing

- 1). Connect the power adapter with the detector's power lines, electrify the detector then it is in working status.
- 2). Press and hold the test button for 3 seconds, LED lights on and send wireless signal, that means the detector work normally. Also you can test it with gas leakage. We suggest that test the detector once per week.

Operation

- 1). Connect the power adapter with the detector's power lines, electrify the detector.
- 2). Press and hold the test button for 3 seconds, it will send wireless registration signal to control panel for wireless network.
- 3). The detector will contact the control panel every 16 hours, or the control panel will report Communication error.

Note

- 1). NOT suitable to install in too cold, too hot, too humid, smoggy, dusty or airflow location.
- 2). Clean the detector surface with soft brush every six month. Disconnect the electricity before cleaning.

Introduction

IDo501W is a wireless gas detector, suitable for installation at gas using place to detect gas leakage. When the smoke exceeds the prescribed concentration, the detector will flash the LED and send wireless alarm signal.

Specification

- Operating Voltage: DC12V
- Current: Static current less than 100mA, alarm current is less than 100mA
- Alarm Concentration: Meet the UL standard
- Alarm Indicator: Red LED
- Alarm Mode: 433MHz wireless signal
- Working Condition: 4°C~50°C

Introduction

- 1). Choose the mounting location after carefully consideration of the detected

- 3). If the detector cannot work normally, please check the power supply connection and clean the detector. Please DO NOT disassemble by oneself, and contact the service centre for professional service.
- 4). It is necessary to install the smoke detector in locations which is prone to gas leakage, like kitchen.
- 5). Gas detector can decrease disaster. For your safety, please use this product correctly.

iDo501W
Wireless Wall Mount Gas Detector



ROISCOK
ROISCOK ELECTRONICS LTD.
www.roiscok.com